

# Trimble R780 Model 2

GNSS SYSTEM

Highly accurate GNSS receiver  
built to handle the toughest  
survey environments.



## Key features

Configurable receiver, scalable for future requirements.

Available in base & rover, rover only, or base only configurations.

Trimble® Inertial Platform™ (TIP™) technology IMU-based tilt compensation for measurement and stakeout.

Trimble IonoGuard™ technology for mitigation of ionospheric GNSS signal disruptions.

Trimble ProPoint® GNSS positioning engine for improved accuracy and productivity in challenging GNSS conditions.

Optional integrated 450 MHz or dual-band 450/900 MHz UHF transceiver.

Trimble Maxwell™ 7 GNSS ASIC.

9 GB internal memory.

Supports Trimble xFill® correction outage technology.

Trimble CenterPoint® RTX corrections for RTK level accuracy worldwide via satellite or internet.

Military-grade ultra-rugged design, IP68 rating.


Optimised for Trimble Access™ field software.



Find out more at:  
[geospatial.trimble.com/r780](https://geospatial.trimble.com/r780)

# Trimble R780 Model 2

GNSS system



## PERFORMANCE SPECIFICATIONS

### GNSS TECHNOLOGY

Constellation agnostic, flexible signal tracking, improved positioning in challenging environments <sup>1</sup> and inertial measurement integration with Trimble ProPoint GNSS technology
Increased measurement and stakeout productivity and traceability with Trimble TIP technology IMU-based tilt compensation
Trimble CenterPoint RTX correction service is activated and ready to use for the initial 12 months. Learn more at <a href="https://rtx.trimble.com">rtx.trimble.com</a>
Advanced dual Trimble Maxwell 7 chipset technology with 672 channels
Trimble EVEREST™ Plus multipath signal rejection
Trimble IonoGuard technology for mitigation of ionospheric GNSS signal disruptions
Spectrum Analyser to troubleshoot GNSS jamming
Anti-spoofing capabilities
Supports Trimble Internet Base Station Service (IBSS) for streaming RTK corrections using Trimble Access 2023.10 or later
Japanese LTE Filtering below 1510 MHz allows antennas to be used 100 m away from Japanese LTE cell tower
Iridium Filtering above 1616 MHz allows the antenna to be used 20 m away from Iridium transfer

### SATELLITE TRACKING

GPS: L1C, L1 C/A, L2E (L2P), L2C, L5
GLONASS: L1C/A, L1P, L2C/A, L2P, L3
Galileo: E1, E5A, E5B and E5AltBOC, E6 <sup>2</sup>
BeiDou: B1, B2, B3, B1C, B2A, B2B
QZSS: L1 C/A, L1C, L1S, L2C, L5, LEX/L6
IRNSS: L5
SBAS: L1 C/A (EGNOS/MSAS GAGAN/SDCM), L1 C/A and L5 (WAAS)
L-Band: Trimble RTX <sup>®</sup>

## POSITIONING PERFORMANCE<sup>3</sup>

### STATIC GNSS SURVEYING

#### High-Precision Static

Horizontal	3 mm + 0.1 ppm RMS
Vertical	3.5 mm + 0.4 ppm RMS

#### Static and Fast Static

Horizontal	3 mm + 0.5 ppm RMS
Vertical	5 mm + 0.5 ppm RMS

### REAL TIME KINEMATIC SURVEYING

#### Single Baseline < 30 km

Horizontal	8 mm + 1 ppm RMS
Vertical	15 mm + 1 ppm RMS

#### Network RTK<sup>4</sup>

Horizontal	8 mm + 0.5 ppm RMS
Vertical	15 mm + 0.5 ppm RMS
RTK start-up time for specified precisions <sup>5</sup>	2 to 8 seconds

### TRIMBLE INERTIAL PLATFORM (TIP) TECHNOLOGY

#### TIP Compensated Surveying<sup>6</sup>

Horizontal	RTK + 8 mm + 0.5 mm/° tilt (up to 30°) RMS
Horizontal	RTX + 8 mm + 0.5 mm/° tilt (up to 30°) RMS

#### IMU Integrity Monitor

Bias monitoring	Temperature, age and shock
-----------------	----------------------------

### TRIMBLE RTX CORRECTION SERVICES

#### CenterPoint RTX<sup>7</sup>


Horizontal	2 cm RMS
Vertical	3 cm RMS
Convergence time for specified precisions in Trimble RTX Fast regions	< 1 min
Convergence time for specified precisions in non Trimble RTX Fast regions	< 3 min
QuickStart convergence time for specified precisions	< 5 min

### TRIMBLE XFILL<sup>8</sup>

Horizontal	RTK <sup>9</sup> + 10 mm/minute RMS
Vertical	RTK <sup>9</sup> + 20 mm/minute RMS

# Trimble R780 Model 2

## GNSS system



### POSITIONING PERFORMANCE<sup>3</sup> Cont.

#### CODE DIFFERENTIAL GNSS POSITIONING

Horizontal	0.25 m + 1 ppm RMS
Vertical	0.50 m + 1 ppm RMS
SBAS <sup>10</sup>	Typically < 5 m 3DRMS

### HARDWARE

#### PHYSICAL

Dimensions (W×H)	13.9 cm × 13 cm (5.5 in × 5.1 in) including connectors	
Weight	1.55 kg (3.42 lb) receiver only including radio and battery	
Temperature <sup>11</sup>		
	Operating	-40 °C to +65 °C (-40 °F to +149 °F)
	Storage	-40 °C to +75 °C (-40 °F to +167 °F)
Humidity	100%, condensing	
Ingress protection	IP68 Certified per IEC-60529: waterproof/dustproof (1 m submersion for 1 hour)	
Shock and vibration		
	Pole drop	Designed to survive a 2 m (6.6 ft) pole drop onto concrete
	Shock	Non-operating: 75 Gs at 6msec
	Shock	Operating: 40 Gs at 10msec
	Vibration	Mil-Std-810G, FIG 514.6E-1 Cat 24, Mil-Std-202G, FIG 214-1, Condition D

#### ELECTRICAL

	Internal	Rechargeable, removable Lithium-ion battery in internal battery compartment Internal battery operates as a UPS during an ext power source failure Internal battery will charge from external power source as long as source can support the power drain and is more than 11.8 VDC Integrated charging circuitry
	External	External power input with over-voltage protection on Port 1 (7-pin Lemo 2-key) Minimum 10.8 V, Maximum 28 VDC, shutdown optimised for 12 V lead acid battery operation Power source supply (Internal/External) is hot-swap capable in the event of power source removal or cut off DC external power input with over-voltage protection on Port 1 (Lemo) Receiver automatically turns on when connected to external power
	Power consumption	3.2 W in rover mode with internal receive radio <sup>12</sup> 5.2 W in base mode with internal 0.5 W transmit radio
Operating times on internal battery <sup>13</sup>		
	Rover	5.5 hours; varies with temperature
	Base station	5.5 hours; varies with temperature
	450 MHz systems	Approximately 4 hours; varies with temperature
	900 MHz systems	Approximately 4 hours; varies with temperature

### COMMUNICATIONS AND DATA STORAGE

Lemo (Serial 1)	7-pin Lemo 2-key, Power Input, USB. Optional USB to RS232 serial cable. Receiver supports RNDIS communications over USB	
Wi-Fi®	Client or Access Point. Receive or transmit corrections. Wi-Fi b/g/n	
Bluetooth® wireless technology	Fully-integrated sealed 2.4 GHz Bluetooth module	
Channel spacing (450 MHz)	12.5 kHz or 25 kHz spacing available	
Sensitivity (450 MHz)	-114 dBm (12 dB SINAD)	
Radio modem	Fully integrated, sealed 450 MHz wide band transceiver with frequency range of 410-473 MHz (RED 2014/53/EU compliant) or dual-band 450/900 MHz transceiver (410 MHz–473 MHz / 902 MHz–928 <sup>14</sup> MHz frequency range)	
	Transmit power	0.5 W, 1.0 W (1.0 W available only where legally permitted) (Note: 1 W is only available if "Transmit High Power" option is enabled)
	Range	3-5 km typical, 10 km optimal
Frequency approvals (410 MHz–473 MHz)	Worldwide, depending on the local required licensing	
Positioning rates	1 Hz, 2 Hz, 5 Hz, 10 Hz, and 20 Hz	
Data storage	9 GB internal data logging	
Data format	CMR+, CMRx, RTCM 2.1, RTCM 2.3, RTCM 3.0, RTCM 3.1, RTCM 3.2 input and output 24 NMEA outputs, GSO, RT17, and RT27 outputs (RTCM output not supported for 900 MHz UHF)	



# Trimble R780 Model 2

GNSS system

## CERTIFICATIONS

FCC Part 15 Subpart B (Class B Device), Part 15.247, Part 90
Canadian ICES-003 (Class B), RSS-GEN, RSS-247
CE mark, UKCA mark
Radio Equipment Directive (RED 2014/53/EU)
RoHS compliance
WEEE compliance
IEC62368-1 3rd Edition
EN62311, EN 55032, EN55035
ACMA mark, AS/CISPR 32
Japan MIC

## TRIMBLE PROTECTED PROTECTION PLANS

Add a Trimble Protected protection plan for worry-free ownership over and above the standard Trimble product warranty. Added enhancements include coverage for wear & tear, environmental damage, and more. Accidental damage is covered with Premium plans, available only at point-of-sale in selected regions. For details, visit [trimbleprotected.com](http://trimbleprotected.com) or contact a local Trimble distributor.

- 1 Challenging GNSS environments are locations where the receiver has sufficient satellite availability to achieve minimum accuracy requirements, but where the signal may be partly obstructed by and/or reflected off of trees, buildings, and other objects. Actual results may vary based on user's geographic location and atmospheric activity, scintillation levels, GNSS constellation health and availability, and level of multipath and signal occlusion.
- 2 The current capability in the receivers is based on publicly available information. As such, Trimble cannot guarantee that these receivers will be fully compatible with a future generation of Galileo satellites or signals.
- 3 Precision and reliability may be subject to anomalies due to multipath, obstructions, satellite geometry, and atmospheric conditions. The specifications stated recommend the use of stable mounts in an open sky view, EMI and multipath clean environment, optimal GNSS constellation configurations, along with the use of survey practices that are generally accepted for performing the highest-order surveys for the applicable application including occupation times appropriate for baseline length. Baselines longer than 30 km require precise ephemeris and occupations up to 24 hours may be required to achieve the high precision static specification.
- 4 Network RTK PPM values are referenced to the closest physical base station.
- 5 May be affected by atmospheric conditions, signal multipath, obstructions and satellite geometry. Initialisation reliability is continuously monitored to ensure highest quality.
- 6 TIP references the overall positioning error estimate at the tip of the surveying pole throughout the tilt compensation range. RTK refers to the estimated horizontal precision of the underlying GNSS position, which is dependent on factors that affect GNSS solution quality. The 8 mm constant error component accounts for residual misalignment between the vertical axes of the receiver and the built-in Inertial Measurement Unit (IMU) after factory calibration, assuming the receiver is mounted on a standard 2 m carbon fiber range pole which is properly calibrated and free from physical defects. The tilt-dependent error component is a function of the quality of the computed tilt azimuth, which is assumed here to be aligned using optimal GNSS conditions. For best IMU tilt compensated results, perform a pole bias adjustment.
- 7 RMS performance based on repeatable in field measurements. Achievable accuracy and initialisation time may vary based on type and capability of receiver and antenna, user's geographic location and atmospheric activity, scintillation levels, GNSS constellation health and availability and level of multipath including obstructions such as large trees and buildings.
- 8 Accuracies are dependent on GNSS satellite availability. xFill ends after 5 minutes of radio downtime. xFill is not available in all regions, check with your local sales representative for more information.
- 9 RTK refers to the last reported precision before the correction source was lost and xFill started.
- 10 Depends on SBAS system performance.
- 11 Receiver will operate normally to -40 °C, internal batteries are rated from -20 °C to +60 °C (ambient +50 °C).
- 12 Tracking GPS, GLONASS and SBAS satellites.
- 13 Varies with temperature and wireless data rate. When using a receiver and internal radio in the transmit mode, it is recommended that an external 6 Ah or higher battery is used.
- 14 900 MHz range only available in select regions.

Specifications subject to change without notice.



Contact your local Trimble Authorised Distribution Partner for more information

**NORTH AMERICA**  
Trimble Inc.  
10368 Westmoor Drive  
Westminster CO 80021  
USA

**EUROPE**  
Trimble Services GmbH  
Am Prime Parc 11  
65479 Raunheim  
GERMANY

**ASIA-PACIFIC**  
Trimble Navigation  
Singapore PTE Limited  
3 HarbourFront Place  
#13-02 HarbourFront Tower Two  
Singapore 099254  
SINGAPORE

